

# BlueRange Gateway V3

## Datasheet

IoT Edge Computing Device for connecting a BlueRange Bluetooth Low Energy (BLE) mesh infrastructure with a BlueRange Server cluster.

Item number: BR-MGW-2020-00002-1



## BlueRange Gateway V3

### Overview

- Gateway device between BLE infrastructure and BlueRange server cluster
- Optimized for devices with BlueRange firmware
- Conversion of BLE input messages to MQTT output messages
- Power input via Power-over-Ethernet (PoE) or USB type C 5.1 V / 3 A DC

### Specification, Characteristics

|                                   |  |
|-----------------------------------|--|
| Type                              | Mesh Gateway   |
| Item number                       | BR-MGW-2020-00002-1  |
| Power supply                      | Power-over-Ethernet (PoE) or Micro USB type C  |
| Power PoE                         | 5.1 V / 3 A / 802.3af compliant  |
| Power USB type C                  | 5.1 V / 3 A DC   |
| Processor                         | Broadcom BCM2837B0, Cortex-A53 64-bit SoC @ 1.4 GHz  |
| Memory                            | 1GB LPDDR2 SDRAM, microSD support  |
| Connectivity                      | WLAN 802.11 b/g/n/ac (2,4 + 5,0 GHz), Bluetooth 4.2, BLE, LAN RJ45 Port for 10/100/1000 MBit/s, MicroSD slot, 4 x USB2.0, 3,5 mm AUX jack, HDMI, Micro USB |
| Geometry (L/W/H)                  | 100 / 70 / 40 mm   |
| Weight                            | ca. 162 g  |
| Operating and storage temperature | 5 - 50 °C  |
| Protection class                  | IP20   |



## Connection

The gateway is connected with a power source via ethernet cable for Power-over-Ethernet (PoE) power supply by the 802.3af standard with an input power of 36-56 V and output of 5 V or via a USB-C cable, as long as the source delivers 5 V / 2.5 A DC.

Connect the ethernet cable to the ethernet port of the gateway and then to your router. Connect the Micro USB type C power cable to the Micro USB type C port of the gateway and then to your power socket / power source.

The gateway is connected to a network via ethernet cable or via WiFi. To connect to a network please ensure that the gateway is able to communicate within this network by checking the "Infrastructure Setup" document for correct ports and IPs. To easily connect and enroll a gateway, use the BlueRange Commissioning App. There you are able to give network information, such as Static IP, WiFi credentials, Proxy information.

The connection to the BLE mesh infrastructure is determined by the enrollment.

## Functional Description

The BlueRange Gateway Edge Computer is used for all kind of IoT installations utilizing Bluetooth Low Energy communication on the one side and connection to the internet on the other.

Standard recommendation for connected BLE devices is 100 pieces. However, it is also possible to connect and manage more devices. The more devices there are in a single closed BLE mesh, the higher the latency for a complete penetration of the mesh with information, depending on the number of hops between the BLE nodes or devices.

Depending on the type of different use cases in parallel, the data traffic is according within the mesh and from the gateway into the connected cloud systems or server cluster. Since the gateway itself is also a mesh participant, it must be within the communication range of at least one mesh node to be able to connect with the mesh.

## Order Information

BlueRange Gateway V3



Item number: BR-MGW-2020-00002-1

In standard application used for BlueRange installations of BLE mesh infrastructure and comes with BlueRange OS and Firmware.

One year legal warranty.

No cables included.

## Signs and certificates

|   |  |
|---|--|
|  | <p>WEEE directive 2012/19/EU<br/>Do not dispose of with household waste!</p>   |
|  | <p>CE certification - Conformité Européenne<br/>Declaration in accordance with EU Regulation 765/2008 that the product complies with the applicable requirements laid down in the Community harmonisation legislation on its affixing.</p> |

## Related Components

Our BlueRange Gateway is compatible with several **BlueRange Ready** components by other manufacturers. See examples below:

---

### **Vossloh-Schwabe Deutschland GmbH – Blu2Light series**



All components of the Blu2Light series are fully BlueRange Ready and used to setup lighting installations.

The LiNA configuration and user apps are fully BlueRange integrated and concpeted

[vossloh-schwabe.com/blu2light-indoor](https://vossloh-schwabe.com/blu2light-indoor)

---

### **Regent Beleuchtungskörper AG – Lightpad Tuneable series**



Regent Lighpad Tuneable office luminaires connect to a BLE mesh via BlueRange Mesh.

These luminaires can be controlled and managed via an App and/or connect to a cloud via a gateway.

[regent.ch/lightpad-tunable](https://regent.ch/lightpad-tunable)

---

### **Herbert Waldmann GmbH & Co. KG / LIZ – YARA series**



The YARA luminaire series luminaires connect to a BLE mesh via BlueRange Mesh.

These luminaires can be controlled and managed via an App and/or connect to a cloud via a gateway.

[waldmann.com/yara](https://waldmann.com/yara)

---

**Find** more **BlueRange Ready** products at:

[bluerange.io/components](https://bluerange.io/components)

## Further information and tools

Please find our documentation on how to setup and enroll a BlueRange BLE mesh infrastructure at [bluerange.io/developer](https://bluerange.io/developer).

## Link to the BlueRange Provisioning App:



## Contact:

### Technical question:

[info@bluerange.io](mailto:info@bluerange.io)

### Inquiries:

[sales@bluerange.io](mailto:sales@bluerange.io)

### General information on BlueRange

[www.bluerange.io](https://www.bluerange.io)

## Disclaimer

Subject to change without notice. All data without guarantee.

The data sheet refers to the current factory setting.

The function in installations with other devices must be checked in advance for compatibility.